



Merit LILIN Ent. Co., Ltd.

LILIN DHD DVR control over HTTP integrate

July 1st, 2016

Syntax:

http://<serverIP>/?f=ir:<COMMAND>

Example: Send Menu Command

http://<user>:<pass>@192.168.0.111/?f=ir:95

<user>, default username is "admin".

<pass>, default password is "pass".

Mapping table of the remote control of LILIN AHD DVR

Operation	Remote Control Key	Hex Code	COMMAND	Description
REC	Record	0x0B	11	
None	Lock	0x0C	12	
CAMREA 1	1	0x1F	31	
CAMREA 2	2	0x1C	28	
CAMREA 3	3	0x1D	29	
CAMREA 4	4	0x1A	26	
CAMREA 5	5	0x59	89	
CAMREA 6	6	0x40	64	
CAMREA 7	7	0x16	22	
CAMREA 8	8	0x46	70	
CAMERA 9	9	0x19	25	
CAMERA 10	0	0x0D	15	
CAMERA +10	Plus10	0x 4B	75	
SETUP	MenuPause	0x5F	95	
ESC	Escape	0x4F	79	
UP	UpSlow	0x5B	91	
DOWN	DownStop	0x5C	92	
LEFT	LeftRewind	0x5E	94	
RIGHT	RightForward	0x4E	78	
ENTER	EnterMode	0x5A	90	
PLAY	Play	0x57	87	
GO PRSET 129	Preset	0x56	86	
PIP CAMERA 1	PIP	0x41	65	
None	OSD	0x52	82	Reserve for future
SEQ	Auto	0x05	5	Sequence Display
IRIS OPEN	IrisOpen	0x02	2	
SPRAY	Zoom	0x4A	74	Digital Zoom Menu
WIPER	PTZ	0x53	83	PTZ Menu
None	Tour	0x00	0	Reserve for future
IRIS CLOSE	IrisClose	0x54	84	
DIV. 4	2x2	0x5D	93	
DIV. 9	3x3	0x4D	77	

None	13CH	0x55	85	
DIV. 16	4x4	0x06	6	
	Mute	0x01	1	