

## **Merit LILIN Application Note**

# How to display one NAV's desktop live video into another physical NAV's channel.

Document Number: A00132 Date: 08/14/2017 Dept: Technical Support, Taipei

**Subject:** This document describes how to display one NAV's desktop live video into another physical NAV's channel.

#### **Requirements:**

Navigator Enterprise V2.0.0.22 or above. At least two PCs with Navigator Enterprise installed



Settings: Please follow steps as below.

PC #1

- 1. Launch Navigator from a PC you would like to capture the desktop.
- 2. Click Navigator MStreaming Server 64Bits icon, and then select Setup page.



Cam 023 Cam 024		ดิ
Navigator MStreaming Server 64 Bits	~	
Log Setup	Ö	0
Log 2017/08/09 17:08:38 [Streaming Server Start.] 2017/08/09 17:08:38 [IP Address: 192.168.3.71 login in 1/512] 2017/08/09 17:08:38 [Single Live Streament Generat] #001 IBC0523]]	¥	0
2017/08/09 17:08:38 [JD[0] Command OK: getstream000&smallstream&iframeonly=1] 2017/08/09 17:09:24 [IP Address: 192.168.3.71 login in 2/512] 2017/08/09 17:09:24 [Single Live Streaming Connect[#001 IPC0522]] 2017/08/09 17:09:24 [D[1] Command OK: getstream000&smallstream&iframeonly=1]	SEQ	÷.
<u>د الله الله الم الم الم الم الم الم الم الم الم الم</u>		
Fvit		
Naviastar MSt	reaming Ca	war 6/1 Bite
		= 05-10
CH 🚔 🗸 🔤 🗟 🗟 🗟 🖉 💭 🕪	20:	17/8/9

3. Click the Setup Screen Capture button.

og Setup		
Net Streaming Server	Listen Port	8021
IPScan Discovery Support		
Service Configuration		
Setup Screen Capture		
		Server Start
		Server Stop



4. Check Enable Screen Capture Streaming, and then click the OK button.

Image C	Quality: 6						
High		(N. 14) 	<i>T</i> .(	14 - 41	1) II	(a)*	Low
Max Fra	mes Per Second:	16					
	-			-0	<u>k</u>		<u></u>

### On Navigator PC #2

5. Launch Navigator, on the live display mouse right click and select Properties for entering the below settings.



- 6. Set Device Type to Manual.
- Key in a command 192.168.3.61/?cmd=screencapture&capmon=1 after IP/DNS. The IP address belongs to PC1. capmon=1 which means PC1's monitor 1, so if you would like to capture image from the 2<sup>nd</sup>. monitor, you could change the number 1 to 2. (The capmon number is up to 8)
- 8. The HTTP Port: 8021(default).



9. Key in the PC1's NAV username and password.

Click OK button.

Display/Record			Preview			
Activate this device						
Name	Cam 005					11.11.01.1
Channel Location			њ.			
Device Type	Manual	- Detect	96,61,94 91,0	Stin	Jacii I	*LE.FV
Frame Rate		- ONVIF	+6.5.3% +6.5	Levi addition and the second s		
Channel		7		- Carlo and a second		یا تھا ۔ جانب کا ا
Enable Recording	Auto import DVR	Setting	PLALING (FL)			91.60.00 đ
Low Bitrate Recording	Mode 1 FI	PS +		"Science action to "Science"         1		
Network			NL/LEW TL	LIN PLILIN P	elicitic realian	
Network IP/DNS HTTP Port (ex. 80)	192.168.3.61/?cmd=scre	eencapture&	Find D	env eller e	vicine vicitary	eccent
Network IP/DNS HTTP Port (ex. 80) Video Port	192.168.3.61/?cmd=scre 8021 554	eencapture&	Find D	ection +	uncre eccluse	ec
Network IP/DNS HTTP Port (ex. 80) Video Port Username	192.168.3.61/?cmd=scre 8021 554 admin	eencapture&	Find D	vevice	Vid	leo
Network IP/DNS HTTP Port (ex. 80) Video Port Username Password	192.168.3.61/?cmd=scre 8021 554 admin	eencapture&	Find D	eevice	Vid Alarm Mar ePOS	leo nagement
Network IP/DNS HTTP Port (ex. 80) Video Port Username Password Camera/485 ID	192.168.3.61/?cmd=scre 8021 554 admin 1	eencapture&	Find D Find D Auto switch th ONVIF Device Type: Alarm Input (DI):	eve exact of the sudio	Vid Alarm Mar ePOS ANPR Gro	ieo nagement iOSD up Setting
Network IP/DNS HTTP Port (ex. 80) Video Port Username Password Camera/485 ID	192.168.3.61/?cmd=scre 8021 554 admin 1	Apply	Find D Find D Auto switch ti ONVIF Device Type: Alarm Input (DI): Relay Output (DO	eve even even even even even even even	Vid Alarm Mar ePOS ANPR Gro Object C	leo nagement VOSD up Setting Counting

Then leave the camera setting and you should see on one channel the desktop of the first PC In our example, channel 4 show the navigator of the first computer





If you double click on the new channel will display it in full screen.

- OLILINI							? – 🗆 🗙
•LER	Cam 002		Cam 004	Com 955 Video Loss	Cam 00	Cam 004 ? × 2017/08/16 19.41.07 C.74% CPU: 17% REC PTZ MC OFF MUTE admn R.DAY: 1.67	2017/08/16 10.42:34 C.56% CPU: 24% REC MIC OFF MUTE admin R.DAY: 0.92
Can 607	Cam 008	Cam 000	Cam 010	Cam 012	Cam 01: OLILINI	30	Applications
Cam 013 OLILINI	Cam 014 O L. IL IN A	Cam 015 <b>&amp; L.I.L.IN.I</b>	Cam016	Cam 017 O <b>L. IL. IN I</b>	Cam OII O <i>LILINE</i>	<ul> <li>Applications</li> <li>Groupings</li> <li>Windows</li> <li>Playback</li> </ul>	Groupings
Cem019 OLILINI	Cem 030	Cəm ÖZİ <b>OLILINI</b>	Cam 022	Cam 023 O <i>LILINI</i>	Cam 02 O L.IL.IN		▲ ■ ○ *○ ♀ ©
Cam 023	Cam 026	Cam 027	Cam 028	Cam039 GLILINI	Cam ON	SEQ 🌲	SEQ 📻
Can 031	Cam 032 GLILINI	Com 033	Cam 014	Cam 035 OLILINI	Cam 0X		

#### Contact

Contact lilin.zendesk.com for technical support.