

# Merit Lilin Technical Support Document

Document Number: Q00029  
Date: 1/09/2009  
Dept: Technical Support, Taipei

**Subject:** How to embed QuickTime player into an HTML web page for live video of IP cameras.

**Firmware Requirement:**

Firmware version 0.3.28 or above is required.

**Product Supported**

IPS025/030/035, MI025/030/035, PS203/212, IPR454/8, VS012, IPD552

**Summary:**

This document describes the way for embedding QuickTime into an HTML for live video of Merit LILIN H.264 IP Cameras/Video Server.

Step #1: Copy and paste the following code into your HTML file.

```
<html>
<head>
<title>Merit LILIN H.264 Demo Page</title>
</head>

<body>
<form name = "thisform">
<script language="JavaScript">
document.writeln('<OBJECT CLASSID="clsid:02BF25D5-8C17-4B23-BC80-D3488ABDDC6B" width=' + 720 +
' height=' + 480 + ' CODEBASE="http://www.apple.com/qtactivex/qtplugin.cab">');
document.writeln('<param name="autoplay" value="true">');
document.writeln('<param name="controller" value="true">');

//H.264 over RTSP over HTTP 80 port
document.writeln('<param name="qtsrc" value="" + 'rtsp://59.124.49.45:80/rtspH264' + ">');
//H.264 over RTSP over TCP 554 port
//document.writeln('<param name="qtsrc" value="" + 'rtsp://59.124.49.45:554/rtspH264' + ">');

//JPEG over RTSP over HTTP 80 port
//document.writeln('<param name="qtsrc" value="" + 'rtsp://59.124.49.45:80/rtspJPEG' + ">');
//JPEG over RTSP over TCP 554 port
//document.writeln('<param name="qtsrc" value="" + 'rtsp://59.124.49.45:554/rtspJPEG' + ">');

</script>
</body>
```

Step #2: Upload the above file into a web server.

Step #3: Open a browser for accessing the HTML file via web server.

